READ ME FIRST

Order Number: AV-MC09D-TE

This is VAX REMS Version 1.2. This release takes care of problems existing in version 1.1. This version also has the ability to interface with the HA3000 UPS, and to start up automatically when the VAX system is re-booted. A more detailed explanation of the changes and additions to VAX REMS Version 1.2 can be found in the on-line release notes.

1 Release Notes Information

For a smooth installation, it is recommended that you first extract and read the release notes before attempting to install VAX REMS Version 1.2. To do this, follow the instructions for installing VAX REMS in Section 5 in the Installation Guide, making sure that you specify OPTIONS N as part of the command line. For example, if you were installing VAX REMS from the tape drive, you might type:

```
$ @SYS$UPDATE:VMSINSTAL REMS012 MUA0: OPTIONS N
```

Then, follow the instructions up to step 4 (Section 5.7), and select NO when asked if you want to continue the installation.

2 H731x Preparation

Before installing and running VAX REMS V1.2 on your VAX system, the H731x units must be running VII.4 of the system firmware. Determine the firmware version by pressing the <RESET> key on the H731x keypad. If the unit does not have a keypad, contact your local Digital Field Service Office for assistance.

When the <RESET> key is pressed, the software displays this message:

```
No Alarms Present
 Time of Last Reset 12-04-89 12:58:50
Operational Status : Normal
  --Enter "#" Key for Main Menu    --
  Unit # 0 CHANGE READY REMOTE
Digital Equipment Corporation Ver II4   <-- Version Number
Serial No. TYPE313II4     50.00 KVA
Thursday December 04  1989   13:01:37
```

If you do not have the appropriate firmware, contact your local Digital Field Service Office.

3 Cable Requirements

The H731x and HA3000 products all require the same cable to connect them to a VAX. This is an RS232 cable, part number BC22D-50, or the equivalent. If you are using a DECserver to communicate with the H731x or HA3000 products, the RS232 cable is still required.

To order the correct cable(s), contact your local Digital Sales Office or DEC DIRECT (1-800-DIGITAL).

Copyright (c) Digital Equipment Corporation, 1990. All rights reserved.